


The Single-Port Chassis (120V ONLY) allows the user to use a wide variety of MINUTEMAN option cards with MINUTEMAN UPS' that are not equipped with an internal option slot. The "Ring ON/Rest feature allows the user to remotely reset the Single-Port Chassis via telephone.

Single-Port Chassis



Installation Procedure of the Single-Port Chassis

1. Turn off all the equipment that is plugged into the UPS.
2. Turn off the UPS and unplug the UPS's power cord from the wall outlet.
3. Connect one end of the RS232 serial cable to the DB9 connector on the rear panel of the UPS.
4. Connect the other end of the RS232 serial cable to the DB9 connector on the rear panel of the Single-Port Chassis labeled "To UPS".
5. Connect the Power Adapter to the connector, labeled "INPUT", on the rear panel of the Single-Port Chassis.
6. Plug the other end of the Power Adapter to the "Battery Backup" receptacles on the rear panel of the UPS.
7. Install the option card into the option slot on the Single-Port Chassis.
8. Install the retaining screws for the option card (provided with the option card).
9. See the individual option card User's Manual for the cable connections and setup instructions.
10. Turn the UPS and your equipment ON.
11. The Single-Port Chassis is operational.

Ring ON/Reset Feature

1. Connect the incoming single line phone to the RJ11 connector on the rear panel of the Single-Port Chassis labeled "IN".
2. Connect one end of another telephone cable (not provided) from the RJ11 connector on the rear panel of the Single-Port Chassis labeled "OUT" to the telephone.
3. When the Single-Port Chassis is ON, two incoming rings will reset the Single-Port Chassis. When the Single-Port Chassis is OFF, two incoming rings will turn on the Single-Port Chassis.

Contents of the Single-Port Chassis Package

1. Single-Port Chassis.
2. Power Adapter.
3. One DB9 Male-to-Female Serial Cable (connects from the Single-Port Chassis's RS232 connector to the UPS).
4. User's Manual.

LIMITED PRODUCT WARRANTY

Para Systems Inc. (Para Systems) warrants this equipment, when properly applied and operated within specified conditions, against faulty materials or workmanship for a period of three years from the date of original purchase by the end user. For equipment sites within the United States and Canada, this warranty covers repair or replacement of defective equipment at the discretion of Para Systems. Repair will be from the nearest authorized service center. Replacement parts and warranty labor will be borne by Para Systems. For equipment located outside of the United States and Canada, Para Systems only covers faulty parts. Para Systems products repaired or replaced pursuant to this warranty shall be warranted for the remaining portion of the warranty that applies to the original product. This warranty applies only to the original purchaser who must have properly registered the product within 10 days of purchase.

The warranty shall be void if (a) the equipment is damaged by the customer, is improperly used, is subjected to an adverse operating environment, or is operated outside the limits of its electrical specifications; (b) the equipment is repaired or modified by anyone other than Para Systems or Para Systems-approved personnel; or (c) has been used in a manner contrary to the product's operating manual or other written instructions.

Any technical advice furnished before or after delivery in regard to use or application of Para Systems's equipment is furnished without charge and on the basis that it represents Para Systems's best judgment under the circumstances, but it is used at the recipient's sole risk.

EXCEPT AS PROVIDED HEREIN, PARA SYSTEMS MAKES NO WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. Some states do not permit limitation of implied warranties; therefore, the aforesaid limitation(s) may not apply to the purchaser.

EXCEPT AS PROVIDED ABOVE, IN NO EVENT WILL PARA SYSTEMS BE LIABLE FOR DIRECT, INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OF THIS PRODUCT, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE. Specifically, Para Systems is not liable for any costs, such as lost profits or revenue, loss of equipment, loss of use of equipment, loss of software, loss of data, cost of substitutes, claims by third parties, or otherwise. The sole and exclusive remedy for breach of any warranty, expressed or implied, concerning Para Systems's products and the only obligation of Para Systems hereunder, shall be the repair or replacement of defective equipment, components, or parts; or, at Para Systems's option, refund of the purchase price or substitution with an equivalent replacement product. This warranty gives you specific legal rights and you may also have other rights, which vary from state to state.

Longer term and F.O.B. job site warranties are available at extra cost. Contact Para Systems (1-972-446-7363) for details.